



Date: 17.09.1993

CO - PB02 PRODUCER BOX



CO-PB02 is a combined producercommand and an interviewbox for interviews when working self-up. There is a connection for headset with volume control and a microphone for talkback to studio via KDO-button or interview via INT-button is connected to the XLR at the end of the gooseneck. The INT-button can also make a connection for ON AIR light.

KDO: The commandbutton is black with non-locking action. You can talk to the Studio headsets when pressing this button (via the tabs on the mixer).

INT: The interviewbutton is red with locking action and routes the microphone permanently to the XLR male connector. It can be connected to a spare microphone module on the mixer and named Producer/interview channel.

You get a redlight signal on a seperate 2-way cable, via the channel microswitch.

When using the CO-SCC103 Studio Control you connect this cable to the remote connector marked DIV using the contacts marked Produsent a- and b-rail.

The female XLR-connector is for getting signal to the producerheadset. When using the CO-SCC103 Studio Control Center you connect this to the output marked PROD. You'll get a summation of the two microphone channels in the mixer You have choosen to let the coughbutton activate.

Mikkelsens Elektronikk



CONNECTIONS:

- HEADSET ¼”Stereojack
Sleeve: Earth
Ring: Signal
Tip: Signal

- PROD XLR-3F Cable
Pin 1: Chassis
Pin 2: Signal
Pin 3: Earth

- MICROPHONE XLR-3M Cable
Pin 1: Earth
Pin 2: +Signal
Pin 3: -Signal

If any cable are too short You can use common microphone cables with XLR-connectors to add length to them.

